



www.riso.co.za

POWER PEDESTAL



POWERPEDESTAL



*Compatible Models: CZ, CV, EZ, MZ, RZ, SF, SFII

SPECIFICATIONS

INPUT	220V AC ($\pm 35\%$) 50Hz	
OUTPUT	220V AC, 50Hz Stabilised, Pure Sine Wave	
BATTERY CHARGING	0 – 15 Amp Automatic self-test, charge and discharge	
LCD DISPLAY	Input Voltage	Battery Capacity
	Output Voltage	Load Capacity
	Frequency	
SAFETY	Output overload protection	Input high-voltage protection
	Output short-circuit protection	Input low-voltage protection
	Battery reverse polarity protection	Overheat protection
OPERATING ENVIRONMENT	Temperature: 0°C ~ 40°C Humidity: 10% ~ 90%, non-condensing Altitude: $\leq 4000\text{m}$	

BACKUP CAPACITY

The inverter unit is a 30 watt inverter, and is designed to work with all RISO duplicators.

The Power Pedestal has the backup capacity to make approximately 7,000 prints.

If the Risograph and the Power Pedestal are switched off after each print job, the print quantity will be increased considerably.

Because there is no warm up time, the machine and pedestal must be switched off when not in use.

Because the components of the pedestal draw power when not in use, the machine and pedestal must be switched off when not in use.

OPTIONAL:

The Power Pedestal can be supplied with or without batteries.

The batteries supplied by RISO are SA-CB CSB SEALED BATTERY.

The minimum specification is 2 x 17Ah batteries.

Batteries can be sourced locally by your RISO agent. A higher specification battery can lead to a higher volume of printing.



Contact Details for your RISO Agent: